

Contact Ratings

20 Amp Res @277 VAC
1HP@ 120 VAC
2HP@ 277 VAC
20 Amp Ballast N/O @ 120/277 VAC
10 Amp Ballast N/C @ 120/277 VAC
10 Amp Tungsten N/O @ 120 VAC
770 VA Pilot Duty @ 120 VAC
1,110 VA Pilot Duty @ 277 VAC

Control Input

1 mA @ 12VDC

Contact Output

2 Orange Wires

Power Input

2 White/Black Wires


Power Input Rating

42 mA @ 120 VAC



72A00-1

Hardwired Load Control Module



Yellow jumper from switch selects N/O or N/C

LED ON: Controller Output on.

**CAUTION: RISK OF ELECTRIC SHOCK - MORE THAN ONE DISCONNECT
MAY BE REQUIRED TO DE-ENERGIZE THE DEVICE BEFORE SERVICING.**